

### I. Main technical indexes

- **Working voltage:**DC9V-DC24V(Optional)
- **Working temperature:**-40℃--+80℃
- **Working frequency:**315MHz、433MHz(Optional)
- **Remote control capacity:** 3(learning code and fixed code)
- **Static working current:** ≤7mA
- **Receiving sensitivity:** ≥-105dBm
- **Contact current:** ≤10A
- **Size:** 100x80x27.5mm

### II. Output means

A.Signal momentar: N0.1 key learning.

B.Signal toggle: N0.2 key learning..

C.Signal latch: N0.4 key learning..

D.6-circuit momentar and 6-circuit toggle: N0.4 key learning.

(For details, see the wiring diagram)

### III. Methods and steps for learning

a) Press learning button-buzzer sounds to enter into the learning state.

b) Press any button of the remote control-buzzer sounds twice and it indicates that the learning is success.

### IV. Eliminate stored Information

Long press the learning button for 8 seconds until the buzzer stop sounding, which indicates that the saved information has been cleared successfully.

### V. Wiring Diagram

